



Black Line

Entry control for home and office

by Jantar



Standalone RF receiver – REX A-4-B



Rex A-4-B with RF transmitter REMO

- Standalone access controller with built-in receiver for RF transmitters Remo
- Real time clock and RS-485 communication
- For small and price oriented access control systems
- Designed for both private and public parkings, garages, etc.
- For opening gates, barriers, garage doors, for switching on/off alarm systems, etc.
- Suitable for mounting outdoors
- Internal memory for up to 500 ID devices* /10.000 events
- Anti-tamper alarm
- In standalone mode set-up can be made with a master transmitter, in advanced mode access control software (Blocker, Codeks) must be used
- Possible conversion to an advanced receiver with 26-bit Wiegand output
- OEM and SDK kit available

TECHNICAL DATA

- **Dimensions: 120x95x15mm**
- **Reading frequency: 433MHz**
- **Receiving range: up to 50m**
- **IP65 protection**
- **Internal memory for 1000 ID devices*/ 10.000 events**
- **External power supply 9 to 14V DC (Spider W5, Spider W5-USB/NET, Spider W40B/W40B-NET)**
- **Push button and gate status inputs**
- **Built-in accelerometer (anti-tamper alarm)**
- **Transistor output (500mA)**
- **Max. current consumption 80mA**
- **Operating temperature: from -20°C to +70°C**
- **LED and buzzer for gate status signalization**

* Each button of transmitter Remo is treated as a separate ID device!

ORDERING CODES

Code	Specification
REX A-4-B	Rex A-4 in A-B box, 433MHz
REMO E-V9	RF transmitter in E box, 433MHz

Rex A-4-B - with 8x0,22 alarm cable (3m)