

Products

Assemble kit

EN54 EN54 FireProtect Jeweller detectors

More

Tech specs

EN54 LINE

EN54 FireProtect (Smoke) Jeweller

Wireless addressable point smoke detector



Device compatibility

[Check](#)

Communication

Jeweller communication technology

Proprietary wireless communication technology to transmit commands, alarms, and events.

Key features:

- Two-way communication.
- Advanced sabotage protection.
- Block encryption featuring a dynamic key.
- Instant notifications.
- Remote control and configuration in Ajax apps.

[Learn more](#) >

Frequency bands

866.0–866.5 MHz

868.0–868.6 MHz

868.7–869.2 MHz

905.0–926.5 MHz

915.85–926.5 MHz

921.0–922.0 MHz

Depends on the sales region.

Maximum effective radiated power (ERP)

up to 20 mW

Automatic power control to reduce power consumption and radio interference.

Radio signal modulation

GFSK

Radio communication range

up to 1,700 m

Between the device and control and indicating equipment (CIE) or a range extender in an open space.

[Calculate radio communication range at the facility](#) >

Encrypted communication

All stored and transmitted data is protected by block encryption featuring a dynamic key.

Frequency hopping

To prevent radio interference and jamming.

[Learn more](#) >

Smoke detection

Sensitive element

dual-spectrum optical sensor

Detects smoke based on the size of particles in the air.

False alarm protection

The device does not respond to water vapor.

Patented smoke chamber

Protects the smoke sensor from dust, dirt, and insects.

Additional features

LED indication

- red
- yellow
- green

For indicating detector states: fire alarm, functionality testing, etc.

Installation recommendations

The device is designed for indoor use only.

The SmartBracket mounting panel allows the detector to be rotated up to 90° even after installation.

Sabotage protection

Tamper button

Fault notification when an attempt is made to remove the device from the mounting panel.

[Learn more](#) >

Lock for SmartBracket

to secure the device on the SmartBracket mounting panel

When locked, the lock secures the device and prevents it from being removed without a special tool.



Protection against spoofing

device authentication

Connection loss detection

after 36 s

Detection time depends on Jeweller settings.

Power supply

Battery

2 × CR123A

Pre-installed.

Tool-free battery replacement

To replace the batteries, open the lids of the battery compartments.



Reverse polarity protection

Prevents device damage if the batteries are put in incorrectly.

Recommended battery type

Huiderui CR123A; 3 V; 1,600 mAh,
 LiMnO_2

Calculated battery life

up to 6 years

Enclosure

Dimensions

124 × 124 × 48 mm



Weight

281 g

Operating temperature range

from 0 °C to +50 °C



Operating humidity

up to 80%

48 mm

Protection class

IP20

Flammability rating

UL 94 V-0

Color

Black

White



Complete set

EN54 FireProtect (Smoke) Jeweller

SmartBracket mounting panel

2 × CR123A battery (pre-installed)

Installation kit

Quick start guide

Revision

1

Certification and compliance with standards



EN54 FireProtect (Smoke) Jeweller



Additional information

Compliance with standards

[Learn more >](#)

User manual

[Learn more >](#)

Warranty

24 months

[Learn more >](#)

Subscribe

Subscribe to our emails about secure life. No spam.

[Subscribe](#)

Request extra help

 support@ajax.systems

 @AjaxSystemsSupport_Bot

 Send a request



4,000,000

people worldwide under Ajax protection

Rating 4.7

 Suggest a feature

Products

- [Intrusion protection](#)
- [Video surveillance](#)
- [Fire and life safety](#)
- [Comfort and automation](#)
- [All products](#)
- [Services](#)
- [System integrations](#)
- [Ajax Ready products](#)
- [Fibra wired protocol](#)
- [Ajax radio protocols](#)

Software

- [For users](#)
- [Ajax PRO: Tool for Engineers](#)
- [Ajax Desktop](#)
- [Ajax PRO Desktop](#)
- [Ajax Translator PRO](#)
- [Ajax Cloud Signaling](#)
- [Scenarios](#)



Solutions

- [Customer stories](#)
- [Solutions by facility type](#)
- [Commercial fire detection and alarm system](#)
- [Upgrades and retrofits](#)
- [Why Ajax](#)
- [How it works](#)

Support

- [Manuals and articles](#)
- [Compliance with standards](#)

Tools

- [Ajax device compatibility](#)
- [Video storage calculator](#)
- [Video device calculator](#)
- [Battery life calculator](#)
- [Radio communication range calculator](#)
- [Switches and outlets configurator](#)
- [Fibra power supply calculator](#)
- [All web tools](#)

Connecting to CMS

- [Intrusion alarm monitoring](#)
- [Video monitoring and visual alarm verification](#)
- [Audio alarm verification](#)

Company

- [Blog](#)
- [About us](#)

For partners

- [For partners](#)
- [Ajax Academy](#)

[Press page](#)[Partner Portal](#)[Events](#)[Career](#)[Ajax Next](#)[Students at CES 2026](#)[Reviews and feedback](#) [Hrvatska](#) [Privacy policy](#) [Report a vulnerability](#) [GDPR White Paper](#) [NDAA Statement](#) [Cookie policy](#)[Anti-Spam Policy](#) [End user agreement](#) [Warranty](#)

© 2025 AJAX SYSTEMS CH. All rights reserved