



Entry control for home and office



Capacitive switch button



Button D-C-R

- For unlocking of the doors in access control systems with lower security level in two-way access control (for instance, Button can be used as an exit button instead of exit access control reader for unlocking the door-strike or opening sliding doors)
- An inexpensive way of upgrade onto basic two-way access control where, one-way access control is already implemented
- Button can also be used in any other application where a push button is needed
- Black Line family design
- LED and buzzer for signalization of the door strike status and sound warnings – self driven or controlled by access controller

TECHNICAL DATA

- **Dimensions: 64 (diameter) x 10 mm (height)**
- **Capacitive touch distance: up to 4 mm**
- **External power supply 9 to 14 V DC**
- **Transistor output 0,5 A**
- **Max. current consumption 0,1 A**
- **IP65 protection – suitable for outdoor installation**
- **Operating temperature: from -20 to +70° C**
- **LED and buzzer**
- **LED and buzzer control inputs**

ORDERING CODE

Code	Specification
BUTTON D-C-R	Capacitive switch button with LED and buzzer control input

Button D-C-R - with 6 wires flat cable (25 cm)