



**Jantar**

Entry control for home and office



## Power supply for DIN rail installation with TCP/IP communication converter Spider H20-B



**Spider H20-B**

- Power supply for installation onto DIN rail
- Specially designed for use with advanced controllers Populus H-2-B and H-4-B
- Suitable also for powering of the Rex and Regis controllers, as well as H-Line readers and controllers
- Spider H20 is sufficiently strong to power Populus H with 4 readers and 4 door strikes / 2 electromagnetic locks or 2 Rex or Regis controllers with 2 door strikes / 2 electromagnetic locks
- Additional connectors for communication (RS-485) and powering of the third and fourth controller
- Block connectors for RS-485 communication
- Block connectors for 2 push buttons and 2 door status switches
- Block connectors for 2 door strike outputs
- 2 x 5 A relays, which trigger together with door-strike output
- Built-in RS-485/TCP/IP communication converter

### TECHNICAL DATA

- **Dimensions: 160 x 90 x 62 mm (width 9 modules)**
- **Operating voltage: 110 - 230 V AC, 50Hz**
- **Output: 13,8 V DC (20 W, full time)**
- **Primary fuse: 250V 2,5 A**
- **RS-485 and TCP/IP communication (RJ45)**
- **3 inputs and 3 x 5 A relays**
- **IP21 protection - for indoor installation only**
- **Block connectors for 2 controllers**
- **Power consumption: up to 1W + load**
- **Temperature range: 0 do +40° C**
- **LED status notification**

### ORDERING CODE

Code	Specification
<b>SPIDER H20-B</b>	Power supply for rail installation (20 W) with built-in TCP/IP communication converter