

**S Superior MotionProtect Plus G3 Fibra**

More

**Tech specs****SUPERIOR**

# Superior MotionProtect Plus G3 Fibra

Wired IR motion detector with an additional K-band microwave sensor and anti-masking system

**Device compatibility****Check**

## Communication



## Fibra communication technology

Proprietary wired communication technology to transmit commands, alarms, and events.

Key features:

- Two-way communication.
- Advanced anti-sabotage.
- Instant notifications.
- Remote control and configuration in Ajax apps.

[Learn more](#) >

## Line connection

4-core cable

## Connection

to any point of the Fibra line

The device can be installed behind the hub, detector, keypad, or siren.

## Fibra line length

up to 2,000 m

When using the U/UTP cat.5 twisted pair cable.

[Calculate the line length at the facility](#) >

## Encrypted communication

All stored and transmitted data are protected by block encryption featuring a dynamic key.


## Detection

### Sensitive elements

1 × PIR sensor

1 × K-band microwave sensor

Operating frequency: 24 GHz.



### Motion detection distance

up to 15 m

When installed at a height of 2.4 m.

### Reduced blind zone

up to 0.5 m

Detects a crawling person at a distance of 50 cm from the detector.

### Motion detection angles

horizontal: 90°

vertical: 71°

### Motion detection speed

from 0.1 to 4.0 m/s

The direction of the detector sensors should be perpendicular to an alleged intrusion path into the facility.

## False alarm prevention

- Dual motion detection technology
- SmartDetect

Software algorithm.

## Temperature compensation

Effective motion detection at temperatures from -10 °C to +40 °C.

[Learn more](#) >

## Self-test of sensitive elements

The device checks its sensors' state and notifies if any malfunction is detected.

## Recommendations

It is recommended to install the detector at a height of 2.4 m.

The pet immunity feature is not available for this device.

The device is designed for indoor use only.

## Sabotage protection

## Tamper alarm

3 tampers

Notifications on attempts to detach the detector from the surface or unlock the SmartBracket lock and remove the detector from the mounting panel.



[Learn more](#) >

## Protection against spoofing

device authentication

## Anti-masking system

detects attempts to block the detector view

[Learn more](#) >

## Lock for SmartBracket

To secure the detector on SmartBracket.

## Communication loss detection

after 36 s

Detection time depends on the Jeweller/Fibra settings.

---

## Power supply

## Fibra line

7–30 V<sub>dc</sub>, up to 90 mW

The hub powers the detector.

---

## Enclosure

### Dimensions

120 × 62 × 52 mm



### Weight

156 g

### Operating temperature range

from -10 °C to +40 °C

### Operating humidity

up to 75%



### Protection class

IP30

---

## Colors

White



---

## Complete set

Superior MotionProtect Plus G3 Fibra

SmartBracket mounting panel

Installation kit

Quick start guide

## Certification and compliance with standards



Superior MotionProtect Plus G3 Fibra



## Additional information

## Compliance with standards

[Learn more](#) >

## User manual

[Learn more](#) >

## Warranty

24 months

[Learn more](#) >

## Subscribe

Subscribe to our emails about secure life. No spam.

[Subscribe](#)

## Request extra help

- [!\[\]\(04e1a3144b22fafe75e717d93ed8fdbb\_img.jpg\) support@ajax.systems](mailto:support@ajax.systems)
- [!\[\]\(14ede2c065846f57f1c2f19d3a2035c1\_img.jpg\) @AjaxSystemsSupport\\_Bot](https://twitter.com/AjaxSystemsSupport_Bot)
- [!\[\]\(0fec80124b13a3ac4ff41087a9437eac\_img.jpg\) Send a request](https://helpdesk.ajax.systems)



4,000,000

people worldwide under Ajax protection

Rating 4.7

 [Suggest a feature](#)



## Products



[Intrusion protection](#)

## Software

[For users](#)

Video surveillance  
Fire and life safety  
Comfort and automation  
All products  
Services  
System integrations  
Ajax Ready products

Ajax PRO: Tool for Engineers  
Ajax Desktop  
Ajax PRO Desktop  
Ajax Translator  
Scenarios



## Solutions

Customer stories  
Solutions by facility type  
Upgrades and retrofits  
Why Ajax  
How it works

## Support

Manuals and articles  
Compliance with standards

## Tools

Ajax device compatibility  
Video storage calculator  
Video device calculator  
Battery life calculator  
Radio communication range calculator  
Switches and outlets configurator  
Fibra power supply calculator  
All web tools

## Company

Blog  
About us  
Press page  
Events  
Career  
Reviews and feedback

## For partners

For partners  
Ajax Academy  
Partner Portal