

EN54 EN54 Internal Battery (24h/72h)

More

[Tech specs](#)

EN54 LINE

# EN54 Internal Battery (24h)

Rechargeable Li-ion battery (7.4 V/5 Ah) to install into EN54 Fire Hub Jeweller or EN54 Fire ReX Jeweller

[Device compatibility](#)[Check](#)**Battery type**

## **Battery**

4 × 18650

Rechargeable Li-ion battery.

### **Nominal voltage**

7.4 V<sub>—</sub>

### **Capacity**

5 Ah

---

### **Power supply**

#### **Maximum load current**

3.2 A

#### **End-of-life battery voltage**

6 V<sub>—</sub>

---

### **Power consumption**

#### **Average power consumption with LTE only**

50 mA · h

#### **Average power consumption with Ethernet only**

120 mA · h

## Average power consumption with Wi-Fi only

70 mA · h

## Average power consumption with Ethernet and Cellular (standby)

102 mA · h

## Average power consumption with LTE, Wi-Fi, and Ethernet

140 mA · h

## Recommendations

Use the battery with compatible devices only.


The battery is designed for indoor use only.

---

## Enclosure

## Dimensions

166 × 87 × 23 mm



## Weight

270 g

## Operating temperature range

from -10 °C to +40 °C



## Operating humidity

up to 75% non-condensing



## Protection class

IP20



## Color

Black

White



## Complete set

## Revision

2

## Certification and compliance with standards



EN54 Internal Battery (24h)



## Additional information

### Compliance with standards

[Learn more >](#)

### User manual

[Learn more >](#)

## Warranty

24 months


[Learn more >](#)

## Products

- Intrusion protection
- Video surveillance
- Fire and life safety
- Comfort and automation
- All products
- Services
- System integrations
- Ajax Ready products
- Fibra wired protocol
- Ajax radio protocols

## Software

- For users
- Ajax PRO: Tool for Engineers
- Ajax Desktop
- Ajax PRO Desktop
- Ajax Translator PRO
- Ajax Cloud Signaling
- Scenarios



## Solutions

- Customer stories
- Solutions by facility type
- Commercial fire detection and alarm system
- Wireless Grade 3 solution
- Upgrades and retrofits
- Why Ajax
- How it works

## Support

- Manuals and articles
- Compliance with standards

## Tools

- Ajax device compatibility
- Video storage calculator
- Video device calculator
- Battery life calculator
- Radio communication range calculator
- Switches and outlets configurator
- Fibra power supply calculator
- All web tools

## Monitoring solutions and integrations

- Intrusion alarm monitoring
- Video monitoring and visual alarm verification
- Audio alarm verification

## Company

- Blog
- About us
- Press page

## For partners

- For partners
- Ajax Academy
- Partner Portal

## Subscribe

Subscribe to our emails about secure life. No spam.

[Subscribe](#)

## Request extra help

- ✉ support@ajax.systems
- .telegram @AjaxSystemsSupport\_Bot
- 💬 Send a request



4,000,000

people worldwide under Ajax protection

Rating 4.8

💡 [Suggest a feature](#)



Events

Career

Ajax Next

Students at CES 2026

Reviews and feedback

 Hrvatska   [Privacy policy](#)   [Report a vulnerability](#)   [GDPR White Paper](#)   [NDAA Statement](#)   [Cookie policy](#)   [Anti-Spam Policy](#)  
[End user agreement](#)   [Warranty](#)

© 2026 AJAX SYSTEMS CH. All rights reserved