

[Tech specs](#)

SUPERIOR

# Superior StreetSiren DoubleDeck Fibra

Wired siren with a clip lock for a branded faceplate

[Device compatibility](#)[Check](#)

## Communication

 Fibra communication technology

Proprietary wired communication technology. Fibra combines the reliability of wires with the freedom of radio connection.

It features:

- Two-way communication.
- Advanced anti-sabotage.
- Instant notifications.
- Remote configuration via the Ajax apps.

[Learn more](#)

## Line connection

4-core cable

## Fibra line length

up to 2,000 m

When using the U/UTP cat.5 twisted pair.

[Calculate the line length at the facility](#)


## Encrypted communication

## Key features

## Alarm type

acoustic and LED

Buzzer and LED frame.



## Type of warning device

type Z

External.

## Type of acoustic output

tone

## Alarm volume

from 85 to 113 dB at a distance of 1 m

Adjusted by PRO or user with admin rights in the Ajax app.

## Alarm duration

from 3 s to 3 min

Adjusted by PRO or user with admin rights in the Ajax app.

## Siren sound frequency

$3.5 \pm 0.5$  kHz

## Chime

The siren makes a special sound to notify that the opening detectors are triggered when the system is disarmed.

[Learn more](#) >

## Events indication

- Alerts.
- Entry/exit delays.
- Security mode.
- Security mode changing.
- After-alarm indication.

## Recommendations

The siren is designed for indoor and outdoor use. Recommended installation height is 2.5 m and higher.

---

## Customized branded faceplate

### Brandplate

Security service providers can print their logo and contact information on the siren's front panel.

[Learn more](#) >



## Recommendations

Brandplate is sold separately from street sirens. To place an order, reach out to your regional Ajax [partner](#). You can also compose a faceplate design in the [Brandplate constructor](#).

---

## Sabotage protection

### Tampering alarm

Sends notification if anyone tries to detach the siren from its surface or remove the device from the mounting panel.

[Learn more](#) >

### Protection against forgery

device authentication

## Power supply

### Siren's operating voltage range

7–26 V<sub>dc</sub>, up to 1130 mW

Superior StreetSiren DoubleDeck Fibra is powered by the control panel.

## Siren's nominal operating voltage

24 V=

### Maximum siren's current consumption at nominal voltage

47.1 mA

### Quiescent siren's current consumption at nominal voltage

2 mA

### Peak siren's current consumption at nominal voltage

67 mA

When the siren sounds at the **Very Loud** volume level.

### Average siren's current consumption at nominal voltage

65 µA

When the siren sounds at the default volume level. Regardless of the arming mode.

## Battery

LTO 2.4 V= rechargeable battery

Pre-installed.

### Capacity of the battery

1,500 mAh

The system notifies when the siren battery has 20% of its nominal capacity.

---

## Enclosure

## Dimensions

199 × 199 × 60 mm

199 mm



## Weight of the black device

522 g

## Weight of the white device

531 g

199 mm



## Operating temperature range

from -25°C to +60°C

## Operating humidity

up to 95%

60 mm



## Protection class

IP54, IK07

## Colours

Black

White



---

## Complete set

Superior StreetSiren DoubleDeck Fibra

SmartBracket mounting panel

Installation kit

Quick start guide

## Certification and compliance with standards



Superior StreetSiren DoubleDeck Fibra



## Additional information

[Compliance with standards](#)

[User manual](#)

## Warranty

24 months

[Learn more >](#)

## Products

- Intrusion protection
- Video surveillance
- Fire and life safety
- Comfort and automation
- All products
- Services
- System integrations
- Ajax Ready products
- Fibra wired protocol
- Ajax radio protocols

## Software

- For users
- Ajax PRO: Tool for Engineers
- Ajax Desktop
- Ajax PRO Desktop
- Ajax Translator PRO
- Ajax Cloud Signaling
- Scenarios



## Solutions

- Customer stories
- Solutions by facility type
- Commercial fire detection and alarm system
- Wireless Grade 3 solution
- Upgrades and retrofits
- Why Ajax
- How it works

## Support

- Manuals and articles
- Compliance with standards

## Subscribe

Subscribe to our emails about secure life. No spam.

[Subscribe](#)

## Request extra help

- support@ajax.systems
- @AjaxSystemsSupport\_Bot
- Send a request



Rating 4.8

4,000,000

people worldwide under Ajax protection

[Suggest a feature](#)



## Tools

- Ajax device compatibility
- Video storage calculator
- Video device calculator
- Battery life calculator
- Radio communication range calculator
- Switches and outlets configurator
- Fibra power supply calculator

## Monitoring solutions and integrations

Intrusion alarm monitoring

Video monitoring and visual  
alarm verification

Audio alarm verification

## Company

[Blog](#)

[About us](#)

[Press page](#)

[Events](#)

[Career](#)

[Ajax Next](#)

[Students at CES 2026](#)

[Reviews and feedback](#)

## For partners

[For partners](#)

[Ajax Academy](#)

[Partner Portal](#)